

DIAL COMMAND CODES FOR M1 DIGITAL VOICE SERVICE

(Guide for End User)

∞ Call Waiting	To activate	* 4 3 #
	To verify	* # 4 3 #
	To deactivate	# 4 3 #
To answer 2 nd incoming call	Put 1 st call on hold and answer 2 nd call	Press 'Flash' button and dial '2'
	End 1 st call and answer 2 nd call	Press 'Flash' button and dial '1'
@ Call Divert Unconditional	To activate	* 2 1 * number #
	To verify	* # 2 1 #
	To deactivate	# 2 1 #
Ω@ Call Divert Busy	To activate	* 6 7 * number #
	To verify	* # 6 7 #
	To deactivate	# 6 7 #
@ Call Divert No Reply	To activate	* 6 1 * number #
	To verify	* # 6 1 #
	To deactivate	# 6 1 #
@ Call Divert On User Not Reachable	To activate	* 4 7 * number #
	To verify	* # 4 7 #
	To deactivate	# 4 7 #
Three-Party Voice Conference	Step 1	Call first Callee
	Step 2	Press 'Flash' button and call second Callee
	Step 3	Press 'Flash' button dial '3' to connect all 3 parties

ADDITIONAL NOTES:

Flash Button

- If the phone does not have a 'Flash' button, tap the phone hook

∞ **Call Waiting**

- Deactivate Call Waiting function if you do not wish to receive 2nd incoming call

@ **All Call Divert:**

- Diverts only to fixed line (6xxxxxxx) and mobile number (9xxxxxxx) in Singapore
- Diverting to international number is not supported

Ω **Call Divert Busy**

- Users will still receive the incoming call if Call Waiting function is activated